



KINO FLO
Lighting Systems

FreeStyle

LED



FreeStyle LED DMX



FreeStyle LED has three menu options, one white and two color menus. With white light Kelvin range is from 2700K to 6500K with **Dimming, Kelvin and Green/Magenta** control channels. In the color menu, Kelvin range is from 2500K to 9900K, with three additional channels, **Gel, Hue Angle and Saturation**. The Gel channel includes Kino Flo presets such as blue & green screen and over 100 well-known lighting gels. In addition, the Hue Angle and Saturation behave similar to a traditional color wheel, where you have white light in the center, and the Hue angle determines the color along a 360° range, and Saturation determines how much color is applied. The second color menu provides individual red, green, blue (**RGB**) control. For additional versatility, the FreeStyle LED panel can be easily removed from the housing and mounted onto a stand. The Gaffer Tray accessory allows further flexibility with its slim profile and center mount and screw points. The controller comes with standard DMX, wireless DMX (Lumen Radio®), universal voltage input 100-240VAC and 24VDC. It can be mounted to the fixture or run remotely with a 25ft extension cable.

Features include:

- Kelvin presets & custom settings, 2500K-9900K
- Dimming without color shift
- Green/Magenta control
- Dial in any color through Hue Angle and Saturation control
- Kino Flo presets and Gels
- Individual Red, Green, Blue (RGB) control
- Manual & DMX Dimming, DMX wireless (Lumen Radio)
- Removable fixture includes built-in Barndoors, Honeycomb Louver
- Twist-on, locking Center Mount and corner mount options
- KinoGrip Center Mount

▼ FreeStyle LED DMX Systems



CFX-F31
FreeStyle 31 LED Fixture



CFX-F21
FreeStyle 21 LED Fixture



LED-151X-120U
FreeStyle 151 LED DMX Controller, Univ 120U



LED-151X-230U
FreeStyle 151 LED DMX Controller, Univ 230U



MTP-BG41
KinoGrip 41K Mount w/ Baby Receiver (1.6mm)



X12-25
FreeStyle Extension, 25ft

▼ Photometrics

FreeStyle 31	FC	510	161	75	43	28	20	15	11	9	8
	Feet	2	4	6	8	10	12	14	16	18	20
FreeStyle 21	FC	508	154	70	40	26	18	14	11	9	7
	Feet	2	4	6	8	10	12	14	16	18	20

FreeStyle 31	LUX	7270	2470	1190	683	445	312	233	181	146	117
	Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5
FreeStyle 21	LUX	7113	2409	1121	634	412	288	212	164	131	106
	Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5

▼ Fixture Specifications

Fixture	Kelvin Range	Dimming Range	Dimensions	Weight
FreeStyle 31	2700~6500 2500~9900	100%~1%	40.5 x 3.5 x 11" w/ 6.5" barndoors (103 x 9 x 28cm w/ 16.5cm barndoors)	15 lb (7kg)
Panel 31 Only	2700~6500 2500~9900	100%~1%	37.5 x 2.5 x 9.5" (95 x 6.5 x 24cm)	9 lb (4kg)
FreeStyle 21	2700~6500 2500~9900	100%~1%	26.5 x 3.5 x 13" w/ 6" barndoors (67 x 9 x 33cm w/ 15cm barndoors)	11.5 lb (5kg)
Panel 21 Only	2700~6500 2500~9900	100%~1%	23.5 x 2.5 x 11.5" (60 x 6.5 x 29cm)	6.5 lb (3kg)

▼ LED Controller Specifications

Controller	Input Voltage VAC	Amps VAC	Input Voltage VDC	Amps 24VDC	Kelvin Range	Dimming Range	Dimensions	Weight
LED-151X	100~240VAC, 50/60Hz, 150W	1.25A 0.65A	18~36VDC, 150W	6.25A	2700~6500 2500~9900	100%~1%	15 x 4.5 x 3" (38 x 11.5 x 8cm)	4.5 lb (2kg)

▼ Details



▼ FreeStyle LED DMX Systems



SYS-F31U

FreeStyle 31 LED DMX System, Univ

Contents

- 1 FreeStyle 31 LED Fixture
- 1 FreeStyle 151 LED DMX Controller
- 1 MTP-BG41 Mount w/ Baby Receiver (16mm)
- 1 Extension, 25ft



SYS-F21U

FreeStyle LED 21 DMX System, Univ

Contents

- 1 FreeStyle 21 LED Fixture
- 1 FreeStyle 151 LED DMX Controller
- 1 MTP-BG41 Mount w/ Baby Receiver (16mm)
- 1 Extension, 25ft

▼ FreeStyle LED DMX Accessories/ Cases



DFS-SL30-H
FreeStyle 31 Flozier, Half
DFS-SL20-H
FreeStyle 21 Flozier, Half




DFS-FS31-S
FreeStyle 31 SnapBag
w/ 2x Diffusion
DFS-FS21-S
FreeStyle 21 SnapBag
w/ 2x Diffusion



MTP-L
Kino 41 Lollipop
w/ 3/8" Pin (10mm)



BAG-SL30
FreeStyle 31 Soft Case
BAG-SL20
FreeStyle 21 Soft Case



LVR-SL390-P
FreeStyle 31 Louver/HP, 90°
LVR-SL360-P
FreeStyle 31 Louver/HP, 60°




LVR-FS340-S
FreeStyle 31 SnapGrid, 40°
LVR-FS240-S
FreeStyle 21 SnapGrid, 40°



MTP-B41F
Kino Offset w/
Baby Receiver (16mm)




KAS-DL30
FreeStyle 31 Flight Case
KAS-DL20
FreeStyle 21 Flight Case



LVR-SL290-P
FreeStyle 21 Louver/HP, 90°
LVR-SL260-P
FreeStyle 21 Louver/HP, 60°



FIX-F31T
FreeStyle/GT 31 Gaffer Tray
FIX-F21T
FreeStyle/GT 21 Gaffer Tray



MTP-BAL
Kino Ballast Baby Mount
(16mm)



KAS-FS32
Gaffer/FS 31
Ship Case (2-Unit)
KAS-FS22
Interview/FS 21
Ship Case (2-Unit)




FIX-F31
FreeStyle 31 Fixture Shell
FIX-F21
FreeStyle 21 Fixture Shell



PAN-F31
FreeStyle 31 LED Panel
PAN-F21
FreeStyle 21 LED Panel



STD-M36
Medium Duty, 36"
STD-M30
Medium Duty, 30"



KAS-SL33
FreeStyle 31 Fixture (3)
Ship Case
KAS-SL23
FreeStyle 21 Fixture (3)
Ship Case

FreeStyle LED DMX Kits

▼ FreeStyle 31 LED DMX Kits



KIT-F31BU

FreeStyle 31 LED DMX Kit, Univ w/ Soft Case

Contents	Dimensions
1 FreeStyle 31 LED Fixture	42.5 x 7.5 x 16.5"
1 FreeStyle 151 LED DMX Controller	(108 x 19 x 42cm)
1 MTP-BG41 Mount w/ Baby Receiver (16mm)	Weight
1 Extension, 25ft	29 lb
1 Soft Case	(13kg)



KIT-F31U

FreeStyle 31 LED DMX Kit, Univ w/ Flight Case

Contents	Dimensions
1 FreeStyle 31 LED Fixture	46 x 11 x 16.5"
1 FreeStyle 151 LED DMX Controller	(117 x 28 x 42cm)
1 MTP-BG41 Mount w/ Baby Receiver (16mm)	Weight
1 Extension, 25ft	49.5 lb
1 Flight Case	(22kg)



KIT-F32U

Gaffer/FS 31 LED DMX Kit, Univ (2-Unit)

Contents	Dimensions
2 FreeStyle 31 LED Fixture	43.5 x 13 x 18.5"
2 FreeStyle 151 LED DMX Controller	(110.5 x 33 x 47cm)
2 MTP-BG41 Mount w/ Baby Receiver (16mm)	Weight
2 Extension, 25ft	75 lb
1 Ship Case	(34kg)

▼ FreeStyle 21 LED DMX Kits



KIT-F21BU

FreeStyle 21 LED DMX Kit, Univ w/ Soft Case

Contents	Dimensions
1 FreeStyle 21 LED Fixture	31 x 7.5 x 18"
1 FreeStyle 151 LED DMX Controller	(79 x 19 x 46cm)
1 MTP-BG41 Mount w/ Baby Receiver (16mm)	Weight
1 Extension, 25ft	24.5 lb
1 Soft Case	(11kg)



KIT-F21U

FreeStyle 21 LED DMX Kit, Univ w/ Flight Case

Contents	Dimensions
1 FreeStyle 21 LED Fixture	30 x 10.5 x 21"
1 FreeStyle 151 LED DMX Controller	(76 x 27 x 53cm)
1 MTP-BG41 Mount w/ Baby Receiver (16mm)	Weight
1 Extension, 25ft	39.5 lb
1 Flight Case	(18kg)



KIT-F22U

Interview/FS 21 LED DMX Kit, Univ (2-Unit)

Contents	Dimensions
2 FreeStyle 21 LED Fixture	36 x 13 x 20.5"
2 FreeStyle 151 LED DMX Controller	(91.5 x 33 x 52cm)
2 MTP-BG41 Mount w/ Baby Receiver (16mm)	Weight
2 Extension, 25ft	66.5 lb
1 Ship Case	(30kg)



Kino Flo Lighting Systems
2840 North Hollywood Way
Burbank, CA 91505

+1 818 767 6528 voice +1 818 767 7517 fax

www.kinoflo.com
© Kino Flo FreeStyle LED
No. 3110105 Rev C